

CAVO RADAR HFC-12D SEVICOAX

ATTENUAZIONE A 20°C CON POTENZA MEDIA APPLICATA IN AMBIENTE A 40°C E CONDUTTORE INTERNO A 100°C

FREQUENZA (MHZ)	ATTENUAZIONE dB/100mt	POTENZA MEDIA APPLICATA(KW)
30	1,17	6,19
100	2,17	3,36
150	2,67	2,74
450	4,75	1,56
824	6,49	1,14
890	6,76	1,10
960	7,04	1,05
1000	7,20	1,03
1700	9,61	0,78
1800	9,91	0,76
2000	10,70	0,72
2300	11,54	0,66
3000	14,44	0,58
3400	13,44	0,54
4000	15,81	0,49
5000	17,77	0,44

L'ATTENUAZIONE PUO' AUMENTARE DELLO 0,2% / °C DI SALITA TEMPERATURA AMBIENTE



SEVIKABEL SRL

VIA MARINAI D'ITALIA 1 - 10034 CHIVASSO (TO)

TEL. 011 910.11.12 / 910.67.78 FAX 011 913.13.13 info@sevikabel.it - www.sevikabel.it